

BPS-85-70



Bipolar Power Supply

Model: BPS-85-70

$\pm 85V, \pm 70A$



Features

- High performance bipolar power supply with +/- 85 V, +/- 70 A output
- Full 4-quadrant output operation
- Voltage mode and current mode
- Parallel operation in current mode for +/- 85 V and +/- 140 A
- Very low switching ripple and noise
- Flux gate current transducer for excellent temperature and long term current stability
- Ramp response for different loads tuned from front panel
- Analogue voltage programming of output voltage or current
- Air cooled, 19 " rack mountable package (5 U), 50 kg (110 lb)

Output performance

Output voltage max	± 85 V
Output current max	± 70 A
Output power	6 kW
Switching frequency	250 kHz
Ripple voltage	< 0.2 Vp-p differential
Output noise current	< 1 mArms (0.1Hz...10kHz)

Voltage mode:

Line regulation	< 0.05% (supply voltage min-max)
Load regulation	> 0.1% (output current 0 – max)
Gain drift vs. time	< 0.02% (any 8 hour period after 10 min warm up time)
Offset	< 200 mV
Offset drift vs. time	< 100mV (any 8 hour period after 10 min warm up time)
Gain drift vs. temperature	< 0.02% /°C (10 ... 40°C)
Offset drift vs. temperature	< 20mV /°C
Slew rate	2V/us (load: 2Ω)
Propagation delay	< 20us

Current Mode:

Line regulation	< 0.05% (supply voltage min – max)
Load regulation	< 0.1% (output voltage 0 – max)
Gain drift vs. time	< 0.02% (any 8 hour period after 10 min warm up time)
Offset	< 70 mA
Offset drift vs. time	< 10mA (any 8 hour period after 10 min warm up time)
Gain drift vs. temperature	< 0.02% /°C (10 ... 40°C)
Offset drift vs. temperature	< 10mA /°C
Slew rate	1A/us (load: 2Ω)
Propagation delay	< 20us

Control and monitoring

Input programming, voltage mode	1V/8,5V (+/- 10 V for +/- 85 V) Differential
Input programming, current mode	1V/7A (+/- 10 V for +/- 70 A) Differential
Signal input impedance	30 kΩ

Fault protection: (Output shutdown due to)	Overtemperature
	Overload
	Internal voltages out of tolerance
	IGBT failure
	Internal control failure
	Two external interlocks



Local mode	Voltage or current mode selected via display Voltage or current demand set by knob Enable button for activating the output
Remote mode	Remote mode selected by contact at rear connector Voltage or current mode selected by contact at rear connector Voltage or current demand set by analog signal Enable always on
Tuning	Response for different loads can be finetuned at display
Voltage limit Current limit	Absolute max voltage limit set via display Absolute max current limit set via display

Bipolar
Power Supply

Model:

BPS-85-70

System specifications

Input voltage requirements	180-264VAC 47-63Hz 3-phase Delta, or 3 x 180-264VAC 47-63Hz L1, L2, L3, N Selected by switch at rear panel
Input current	typ. 20A/180VAC 16A/230VAC
Power factor	typ. 0.95/230VAC at full load
Efficiency	0.75 at 6kW output power
Inrush current	typ. 60A@230VAC at cold start
Leakage current	< 2mA/240 VAC
Environmental requirements:	
Ambient temperature	10 °C to 40 °C
Ambient humidity	30 to 70 % non-condensing
Storage temperature	-20 °C to +85 °C
Cooling	Forced air cooling (front in, rear out) Removable dust filter with capability to replace
Unit dimensions:	
Mounting	19" rack. Provision for rack slides
Height	221.45mm (5U, 8.75")
Width	482.6mm (19")
Depth	650mm (25.6")
Weight	50 kg (110 lb)

Regulatory

Designed to meet	EN 61010, UL 61010 AC/DC section: UL60950-1, TUV 60950-1 approved
	CE marked

Company in brief

International Electric Company (IECO) designs and manufactures state-of-the-art electronics for medical, industrial, laboratory and military applications tailored to meet customer needs.

With over 40 years of experience in power electronics we are able to provide solutions for even the most challenging requirements. IECO's quality system is ISO 9001 and ISO 13485 certified.

Power amplifier technology

IECO introduced its first bipolar gradient amplifier in 1994. This revolutionary PWM amplifier enabled excellent image quality in open MRI systems. Simultaneously IECO also launched the first D-class magnet power supply delivering new efficiency levels with 0.1ppm accuracy. IECO's expertise has recently been utilized in the development of the industry's first High Temperature Superconductive MRI magnets.

IECO's power amplifiers are easily scalable for any type of load and any power level needed. Compact amplifier units can be connected in series or in parallel in Master/Slave operation to gain output voltages up to 1100V and output currents over 2000A. Thanks to low-noise, wide bandwidth and excellent step response, IECO has gained the reputation of a technology leader in bipolar gradient amplifiers.

Over 1000 amplifier and magnet power supply systems delivered worldwide.



International Electric Co. Oy
Sahaajankatu 48
00880 Helsinki, Finland

Tel. +358 (0)9 759 4470
Fax +358 (0)9 759 447 57

Email: info@ieco.fi
Internet: www.ieco.fi

North American Distributor:
GMW Associates, 955 Industrial Road,
San Carlos, CA 94070, USA

Phone: +1 (650) 802 8292
Fax: +1 (650) 802 8298

Email: sales@gmw.com
Web: www.gmw.com